

144, 430/440, 1200 MHz ALL MODE TRANSCEIVER



## Direct Sampling Now Enters the VHF/UHF Arena

All mode, tri-band transceiver covering the 144, 430/440 as well as 1200 MHz

Real-time, high-speed spectrum scope for the 144, 430/440, 1200 MHz bands

New PA provides a powerful 100 W (144 MHz), 75 W (430/440 MHz) and 10 W (1200 MHz) output

Dualwatch operation and full-duplex operation in the satellite mode

Follows Icom's center display design style with a 4.3 inch touch screen color TFT LCD

D-STAR provides digital clear audio and Internet capable communication

Smooth satellite operation with normal/reverse tracking and 99 satellite channels

Digital Data (DD) mode provides 128 kbps data communication

# IC-9700

## GENERAL

Frequency coverage:	<USA version> 144.000–148.000, 430.000–450.000, 1240.000–1300.000 MHz
	<EUR version> 144.000–146.000, 430.000–440.000, 1240.000–1300.000 MHz
Mode:	SSB, CW, RTTY, AM, FM, DV, DD
Number of channels:	107 (99 Simplex + 6 Program scan edges + 2 CALL) × 3 bands, 99 (Satellite), 2000 (DR function)
Antenna connectors:	144 MHz SO-239 (50 Ω), 430/440, 1200 MHz Type-N (50 Ω)
Power supply requirement:	13.8 V DC ±15% (Negative ground)
Power consumption:	TX Less than 18 A (High power) RX 1.2 A typical (Standby), Less than 1.8 A (Maximum audio)
Operating temperature range:	–10 °C to +60 °C; 14 °F to 140 °F
Frequency stability:	Less than ±0.5 ppm (–10°C to +60°C; 14°F to 140°F)
Frequency resolution:	1 Hz
Dimensions:	240 × 94 × 238 mm, 9.4 × 3.7 × 9.4 in (W × H × D, projections not included)
Weight:	4.7 kg, 10.4 lb (approximate)

## TRANSMITTER

Output power:	<SSB/CW/FM/RTTY/DV/DD> <AM>	
	144 MHz 0.5–100 W	0.125–25 W
	430/440 MHz 0.5–75 W	0.125–18.75 W
	1200 MHz 0.1–10 W	0.025–2.5 W
Modulation system:	SSB Digital PSN modulation FM Digital Reactance modulation AM Digital Low Power modulation DV Digital GMSK Reactance modulation DD Digital Quadrature modulation	
Spurious emissions:	<Harmonics>	<Out-of-band emission>
	144 MHz Less than –63 dB	Less than –60 dB
	430/440 MHz Less than –61.8 dB	Less than –60 dB
	1200 MHz Less than –53 dB	Less than –50 dB
Carrier suppression:	More than 50 dB	
Unwanted sideband:	More than 50 dB	
Microphone impedance:	600 Ω	

## RECEIVER

Receiver system:	144, 430/440 MHz RF Direct Sampling 1200 MHz Down Conversion IF Sampling	
Intermediate frequency:	311–371 MHz (1200 MHz)	
Sensitivity (Preamp: ON, Filter: SOFT):	SSB/CW (10 dB S/N) Less than 0.11 μV AM (10 dB S/N) Less than 1.0 μV FM (12 dB SINAD) Less than 0.18 μV DV (1% BER) (PN9) Less than 0.35 μV DD (1% BER) (PN9) Less than 1.59 μV	
Selectivity (Filter: SHAPE):	SSB (BW=2.4 kHz) More than 2.4 kHz/–3 dB, Less than 3.6 kHz/–60 dB CW (BW=500 Hz) More than 500 Hz/–3 dB, Less than 700 Hz/–60 dB RTTY (BW=500 Hz) More than 500 Hz/–3 dB, Less than 700 Hz/–60 dB AM (BW=6 kHz) More than 6 kHz/–3 dB, Less than 15 kHz/–60 dB FM (BW=15 kHz) More than 12 kHz/–6 dB, Less than 20 kHz/–60 dB DV (12.5 kHz spacing) More than –50 dB DD (300 kHz spacing) More than –40 dB	
Spurious and image rejection ratio:	SSB/CW 144, 430/440 MHz More than 70 dB, 1200 MHz More than 50 dB AM/FM/DV 144, 430/440 MHz More than 60 dB, 1200 MHz More than 50 dB DD 1200 MHz More than 50 dB	
Audio output power:	More than 2.0 W (1 kHz, 10% distortion) into an 8 Ω load	

## OPTIONS



**HM-219**  
Hand microphone with UP/DOWN switches (Same as supplied)



**PS-126**  
DC power supply (13.8 V DC, 25 A maximum output)




**RS-BA1 (Version 2)**  
IP remote control software



**SM-50**  
Dynamic desktop microphone including [UP/DOWN] switches and a low cut function



**SP-38**  
High quality audio and matching height  
Maximum input: 7 W



**RS-MS1A**  
Remote control application for Android™. Download free from Google Play™.

- **MB-118** Mobile mounting bracket
- **MB-123** Carrying handle
- **OPC-2350LU** PC/Android™ data cable
- **SM-30** Compact, lightweight electret desktop microphone
- **SP-35** External speaker (2 m, 6.6 ft cable)
- **SP-41** External speaker with two input lines
- **CS-9700** Programming software

## SUPPLIED ACCESSORIES

- HM-219, hand microphone
- DC power cable

## REAR PANEL



- A** 144 MHz Antenna Connector
- B** 430/440 MHz Antenna Connector
- C** DC Power Socket
- D** 1200 MHz Antenna Connector
- E** LAN Port
- F** 10 MHz reference signal input
- G** Accessory Socket
- H** Data Jack
- I** USB/B Port
- J** CI-V Remote Control Jack
- K** KEY Jack
- L** External Speaker Jack MAIN
- M** External Speaker Jack SUB
- N** Ground Terminal

D-STAR (Digital Smart Technology for Amateur Radio) is a digital radio protocol developed by JARL (Japan Amateur Radio League). Icom, Icom Inc. and the Icom logo are registered trademarks of Icom Incorporated (Japan) in Japan, the United States, the United Kingdom, Germany, France, Spain, Russia, Australia, New Zealand and/or other countries. This product includes "zlib" and "libpng" open source software, and is licensed according to the open source software license. Android and Google Play are registered trademarks or trademarks of Google Inc. All other trademarks are the properties of their respective holders.

**Icom Inc.** 1-1-32, Kamiminami, Hirano-Ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

[www.icom.co.jp/world](http://www.icom.co.jp/world)

**Count on us!**

**Icom America Inc.**  
[www.icomamerica.com](http://www.icomamerica.com)

**Icom (Europe) GmbH**  
[www.icomeurope.com](http://www.icomeurope.com)

**Icom (Australia) Pty. Ltd.**  
[www.icom.net.au](http://www.icom.net.au)

Your local distributor/dealer:

**Icom Canada**  
[www.icomcanada.com](http://www.icomcanada.com)

**Icom Spain S.L.**  
[www.icomspain.com](http://www.icomspain.com)

**Shanghai Icom Ltd.**  
[www.bjicom.com](http://www.bjicom.com)

**Icom Brazil**  
E-mail: [sales@icombrasil.com](mailto:sales@icombrasil.com)

**Icom (UK) Ltd.**  
[www.icomuk.co.uk](http://www.icomuk.co.uk)

**Icom France s.a.s.**  
[www.icom-france.com](http://www.icom-france.com)